


378M33 MEASUREMENT MICROPHONE

for Acoustic and Electro-Acoustic Test



APPLICATIONS

- Precision sound level measurements
- Research & development
- Hearing preservation and safety
- Leak detection
- Gunshot analysis
- Sound absorption testing

HIGHLIGHTS

- TEDS compliant
- Sensitivity: 2 mV/Pa
- Frequency (± 2 dB) : 5 Hz–80 kHz
- Dynamic range: 42 dBA–165 dB
- Temperature: -40° to $+70^{\circ}$ C
- Polarization: Prepolarized (0 V dc)

STANDARDS COMPLIANCE

- IEC 61094-4 type WS3F compliant
- IEC 61672 class 1 compliant for premium sound level meter use
- IEC 60651 type 1 compliant
- Calibration reference microphone traceable through PTB, compliant with ISO 9001 & 17025, A2LA approved

Audio Precision offers a selection of measurement microphones designed to provide ready solutions for our customers working in acoustic test.

378M33 1/4" measurement microphone system

The Audio Precision model 378M33 is recommended for extreme accuracy applications where high frequency measurements or high acoustic amplitude measurements are required. The 378M33 is a *microphone system*, comprised of a prepolarized microphone capsule combined with a low-noise preamplifier. The preamp is designed to operate on ICP[®] sensor power, and can be used with most 2–20 mA constant current power (CCP) microphone power supplies, including the APx1701. It carries embedded TEDS calibration and identification data; the preamplifier output is available on a 10-32 coaxial (microdot) jack. **Note:** system calibration and TEDS data are valid only for each specific capsule/preamp combination.

Prepolarized free-field measurement microphones


The capacitor (or *condenser*) transducer element in a condenser microphone must carry a charge to function. The 378M33 microphone element is prepolarized to provide this charge, and does not require a polarizing voltage from the power supply, unlike measurement microphones that require a high (often +200 V dc) polarizing voltage. This brings several advantages: less expensive power supplies, simpler two-conductor cabling, and improved performance in high-humidity environments.

A free-field microphone is designed for use in a reflection-free environment such as an anechoic chamber, or out-of-doors. The microphone is compensated for the effect of its presence in the sound field, and should be pointed directly at the sound source (0°).

TEDS (Transducer Electronic Data Sheet) compliant

Each Audio Precision measurement microphone and microphone system is TEDS programmed to the IEEE 1451.4 standard for SMART transducers, V1.0 format. TEDS data contain microphone identification and calibration information that can be read by a connected instrument, such as the Audio Precision APx1701 Transducer Test Interface. Read about the APx1701 on the reverse.

AUDIO PRECISION MODEL 378M33 MEASUREMENT MICROPHONE



Typical free-field response of the microphone with the grid cap at 0 degree incidence. The top curve is the corrected free-field curve, and the bottom curve is the pressure response generated by the electronic actuator.



NOTICE

Prepolarized microphones are a mature and robust technology, but care must be taken when handling any condenser microphone. Avoid removing the grid cap; if this becomes necessary, be careful not to touch the microphone diaphragm. The microphone system calibration includes the microphone capsule and the preamplifier. Use of the capsule with a different preamplifier invalidates the calibration. The capsule and preamplifier are banded with a caution tape as a reminder.

KEY SPECIFICATIONS

Description	1/4" free-field microphone system
Application	Very high frequencies, high level
Nominal Diameter	1/4"
Dimensions	0.28" diameter, 2.07" length
Sensitivity	2.0 mV/Pa
Frequency Range (± 2 dB)	5 Hz to 80 kHz
Inherent Noise	42 dBA re 20 μ Pa
Dynamic Range (3% THD)	165 dB re 20 μ Pa
Mating Connector	10-32 coaxial (microdot)
TEDS Compliant	Yes
Power	CCP 2-20 mA, 10-14 V dc
Recommended Cable	CAB-BNC-MD-10

OPTIONAL ACCESSORIES

APx1701	Transducer Test Interface
CAB-BNC-MD-10	10' BNC to 10-32 microdot coaxial cable
CAB-BNC-3	3' BNC to BNC coaxial cable
079B10	1/4" microphone holder
482A21	ICP® power supply/signal conditioner, 1 channel, unity gain, AC mains powered
480C02	ICP® power supply/signal conditioner, 1 channel, unity gain, battery powered
480B21	ICP® power supply/signal conditioner, 3 channels, x1, x10, x100 gain, battery powered
488B10	AC mains adapter for 480B21
CAL200	Sound level calibrator, 1 kHz, 94 dB SPL and 114 dB SPL, 1/2" diameter
ADP024	1/4" adapter for CAL200
CAL250	Sound level calibrator, 250 Hz, 114 dB SPL, 1" and 1/2" diameter
ADP021	1/4" adapter for CAL250

CALIBRATION AND WARRANTY

Audio Precision measurement microphones are made in the United States. The microphones are manufactured to the highest standards, using a combination of systematic quality control, the finest materials, and clean-room assembly. The products are exposed to an extensive aging program in climate-controlled test chambers to ensure the most stable product. Each unit is qualified and comes with a traceable calibration certification, and is backed by a five-year warranty.

APx1701 TRANSDUCER TEST INTERFACE



If you are making acoustic measurements with your 378M33 and an APx analyzer, consider adding an APx1701 Transducer Test Interface to your setup. The APx1701 provides the correct power to the preamplifier and will read the TEDS data and pass it on to the APx500 measurement software. The 1701 also features a high-performance two-channel power amplifier optimized for acoustic test, switchable hardware for loudspeaker impedance measurements, and complete control and automation integration with the APx500 measurement software.

8211.0346.000

XVIII0306113408



MERSERWIS Sp. z o.o., Sp. K.
www.merserwis.pl
merserwis@merserwis.pl

NIP PL5260058571
REGON 012012494
KRS 0000406516

Gen. Wł. Andersa 10, 00-201 Warszawa
T: +48 22 831 25 21, +48 22 635 82 54
F: +48 22 887 08 52